

ES8000 400V 50Hz

LONG RUN ENERGY



A petrol generator designed specifically for intensive operations where performance power is demanded by professional user, over an extended period of time.

Standard Equipment

| Starting system | | Recoil |
|---------------------------|-------|--------|
| Main Features | | |
| Frequency | Hz | 50 |
| Voltage | V | 400 |
| Power factor | cos φ | 0.8 |
| Single Phase Power factor | cos φ | 0.9 |
| Phase and connection | | 3 |

| Power Rating | | |
|----------------------|-----|-----|
| Standby power LTP | kVA | 8.3 |
| Standby power LTP | kW | 6.6 |
| Continuous power COP | kVA | 7.0 |
| Continuous power COP | kW | 5.6 |

| Single Phase Power Rating | | |
|-----------------------------------|-----|-----|
| Single phase standby power LTP | kVA | 4.0 |
| Single phase continuous power COP | kVA | 3.5 |

Ratings definition (According to standard ISO8528 1:2005)

COP - Continuous Power:

It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedures being carried out as prescribed by the manufacturers.

LTP - Limited-Time running Power:

It is defined as the maximum power available, under the agreed operating conditions, for which the generating set is capable of delivering for up to 500 h of operation per year (whose no more than 300 for continuative use) with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. No overload capability is available.

ΩΡΒΑΠΑ

ES8000 400V 50Hz

Engine Specifications

| Brand | | Honda |
|----------------------------|-----------------|--------------|
| Model | | GX390 Recoil |
| Engine cooling system | | Air |
| Displacement | CM ³ | 389 |
| Aspiration | | Natural |
| Speed governor | | Mechanical |
| Operating Speed-Nominal | rpm | 3000 |
| Oil capacity | L | 1.1 |
| Fuel | | Gasoline |
| Starting system | | Recoil |
| Fuel consumption @ 75% PRP | L/h | 2.15 |



Alternator Specifications

| Class | | н |
|-------------------|---|----|
| IP protection | | 23 |
| Poles | | 2 |
| Voltage tolerance | % | 6 |

Dimensional data

| Length | (L) mm | 729 |
|--------------------|--------|-----|
| Width | (W) mm | 500 |
| Height | (H) mm | 536 |
| Dry weight | kg | 81 |
| Fuel tank capacity | L | 11 |

| Autonomy | | |
|------------------------------|-------|------|
| Running time @ 75% PRP | h | 5.12 |
| Noise level | | |
| Guaranteed noise level (LWA) | db(A) | 97 |
| Noise pressure level @ 7 mt | db(A) | 69 |

ΩΡΒΑΠΑ

ENERGY GENERATION

ES8000 400V 50Hz

GENSET CONTROL

COMMANDS:

- Selector switch: OFF ON
- Starting systems: Recoil
- Fuel Cock

PROTECTIONS STANDARD:

- Thermal protection
- Oil Guard

SOCKET TYPE

| SCHUKO 230V 16A IP54 | 1 |
|--------------------------|---|
| 2P+T CEE 230V 16A IP44 | 1 |
| 3P+N+T CEE 400V 16A IP44 | 1 |



ΩΡΒΑΠΑ

ES8000 400V 50Hz

ACCESSORIES

TRANSPORTATION KIT

with fix handles

TRANSPORTATION KIT

with folding handles





Publishing date: 22/11/13

©2012 | PR INDUSTRIAL s.r.l. | All rights reserved | Image shown may not reflect actual package. Specifications subject to change without notice | ENERGY GENERATION is registered trademarks of PR INDUSTRIAL s.r.l. Other company, product or service names may be trademarks or service marks of others. RevA (06/2012).



www.pramac.com

Generators